

Electronic/Glass Fuses

GGX

- Glass body
- Fast-acting
- 1/4" x 1"



1/2A through 2 1/2A, 250VAC, UL Listed
 3A through 7A, 125V AC, UL Recognized
 8A through 30A, 32V AC, UL Recognized



Standard Fuse Ampere Ratings

| Catalog Number | Ampere Rating | Volts | I.R. |
|----------------|---------------|-------|------|
| GGX1/2 | 1/2A | 250V | 1 |
| GGX3/4 | 3/4A | 250V | 1 |
| GGX1 | 1A | 250V | 1 |
| GGX1-1/2 | 1-1/2A | 250V | 2 |
| GGX2 | 2A | 250V | 2 |
| GGX2-1/2 | 2-1/2A | 250V | 3 |
| GGX3 | 3A | 125V | 3 |
| GGX4 | 4A | 125V | 3 |
| GGX5 | 5A | 125V | 3 |
| GGX6 | 6A | 125V | 3 |
| GGX7 | 7A | 125V | 3 |
| GGX8 | 8A | 32V | 4 |
| GGX10 | 10A | 32V | 4 |
| GGX12 | 12A | 32V | 4 |
| GGX15 | 15A | 32V | 4 |
| GGX20 | 20A | 32V | 4 |
| GGX25 | 25A | 32V | 4 |
| GGX30 | 30A | 32V | 4 |

1. 250VAC @ 35A I.R./125VAC @ 10kA I.R.
2. 250VAC @ 100A I.R./125VAC @ 10kA I.R.
3. 125VAC @ 10kA I.R.
4. 32VAC

GAB

- Ceramic body
- Fast-acting
- 1/4" x 1-1/4"



1/8A through 15A, 250VAC,
 UL Listed and CSA Certified
 20A through 30A, 250/125VAC, UL Recognized



Standard Fuse Ampere Ratings

| Catalog Number | Ampere Rating | Volts | I.R. |
|----------------|---------------|-------|------|
| GAB1/8 | 1/8A | 250V | 1 |
| GAB1/4 | 1/4A | 250V | 1 |
| GAB3/8 | 3/8A | 250V | 1 |
| GAB1/2 | 1/2A | 250V | 1 |
| GAB3/4 | 3/4A | 250V | 1 |
| GAB1 | 1A | 250V | 1 |
| GAB2 | 2A | 250V | 2 |
| GAB2-1/2 | 2-1/2A | 250V | 2 |
| GAB3 | 3A | 250V | 2 |
| GAB4 | 4A | 250V | 3 |
| GAB5 | 5A | 250V | 3 |
| GAB6 | 6A | 250V | 3 |
| GAB7 | 7A | 250V | 3 |
| GAB8 | 8A | 250V | 3 |
| GAB10 | 10A | 250V | 3 |
| GAB12 | 12A | 250V | 4 |
| GAB15 | 15A | 250V | 4 |
| GAB20 | 20A | 250V | 5 |
| GAB25 | 25A | 125V | 6 |
| GAB30 | 30A | 125V | 6 |

1. 250VAC @ 35A I.R./125VAC @ 10kA I.R.
2. 250VAC @ 100A I.R./125VAC @ 10kA I.R.
3. 250VAC @ 200A I.R./125VAC @ 10kA I.R.
4. 250VAC @ 750A I.R./125VAC @ 10kA I.R.
5. 250V/125VAC @ 400A I.R.
6. 125VAC @ 400kA I.R.